



TMdrive®-XL Series Family Product Application Guide

metals

cranes

mining

testing

oil & gas

solar
inverters

power
generation


cement

TMdrive-XL Series




The TMdrive XL series family of variable frequency drives (VFD) provides the high power levels and speed required to drive large motors that power rotating machinery used in the Oil & Gas industry. Important VFD features common to the family include:

- Common architecture, pulse width modulation and control, water cooling, I/O modules, and TMdrive-Navigator programming software
- Multi-level VFD output for smooth waveform to the motor
- 24-36 pulse diode converter rectifier for low harmonic distortion
- High VFD reliability and availability with MTBFs in excess of 20 years and MTTR of less than 30 minutes.
- Output frequency range high enough for direct compressor drive with no gearbox, eliminating costly lube oil systems in addition to the gearbox, resulting in increased system efficiency.
- Up to 7.2 kV supply to the motor with no output transformer required
- Ability to operate drive banks in parallel for higher power levels up to 120 MVA




Three different inverter modules for this architecture, three per VFD:




8 MVA VFD Power Module

Single Phase
Inverter using IGBTs
0.9 kA, 4.5 kV



20 MVA VFD Power Module

Single Phase
Inverter using IEGTs
5.5 kA, 4.5 kV



15/30 MVA Power Module

Single Phase
Inverter using GCTs
6 kA, 6 kV


XL Drive Family Power Expansion

Higher Power Levels. The XL VFDs can be run in parallel to produce higher power levels than single banks. Two, three, or four banks can be combined to obtain the desired power. The example below shows how an XL VFD can be expanded to four banks for a power of 120 MVA (156,000 hp). The table shows the maximum power levels available from the VFD family.

The multi-bank VFDs provide drive and control redundancy for improved reliability.


	XL Drive Power Levels, Single Bank	Multiple Banks, Max
TMdrive-XL85	30 MVA (39,000 hp)	120 MVA (156,000 hp)
TMdrive-XL75	20 MVA (26,000 hp)	80 MVA (104,000 hp)
TMdrive-XL80	15 MVA (19,500 hp)	30 MVA (39,000 hp)
TMdrive-XL55	8 MVA (10,400 hp)	16 MVA (20,800 hp)

One-Bank TMdrive-XL – Power level up to 30 MVA




- Synchronous or Induction motor can control rotating machinery directly for low and high speed applications.

Two-Bank TMdrive-XL – Power level up to 60 MVA



- A redundant control cabinet significantly enhances reliability.
- Synchronous motor can control rotating machinery directly for low and high speed applications; paralleling reactor feeds the motor

Four-Bank TMdrive-XL – Power level up to 120 MVA



- A redundant control cabinet significantly enhances reliability.
- Synchronous motor can control rotating machinery directly for low and high speed applications ; paralleling reactor feeds the motor
- One bank can be redundant to other three banks for increased reliability.

TMdrive-XL Series

TMdrive-XL55 – 8 MVA Frame



- Power Rating:** 8 MVA, expandable to 16 MVA
- Output Voltage:** 6.6 kV
- Output Frequency:** Rated 50-60 Hz, 50 to 250 Hertz option
- Dimensions:** Width 6.5 m
Height: 2.5 m
- Motor type:** Synchronous or Induction



Insulated Gate Bipolar Transistor (IGBT). Rated 4,500 Volts, 900 Amps.




Power Input/Output


Input Voltage	Any utility voltage using separate transformer input 50/60 Hz $\pm 2\%$
Output Voltage	6,600 Vac
Output Current	700 A rms
Output Frequency	50-60 Hz, for over 75 Hz, consult TMEIC
Output Chopping	600 Hz (max)
Efficiency	98.6%
Cable Entry	Bottom or top

Clean Motor Output Wave

As a result of the five-level PWM control, the output current waveform is close to a sine wave. Harmonic currents in the motor windings are minimized so the heat loss is negligible and there is very little shaft torque ripple. Illustrated waveform is from the similar TMdrive XL85 test.



Line-to-Line Voltage at 100% Speed



U-phase Current at 100% Speed

Protective Functions Include:

- Inverter overcurrent
- Inverter overvoltage
- Low system voltage
- Motor ground fault
- Motor overload
- Cooling fan abnormal
- Over-temperature
- CPU error
- Water cooling alarm
- Exciter fault
- DC voltage drop
- Motor inverse rotation
- Stall detection
- Ground detection



Power Circuits

Converter

- AC-fed 36-pulse diode rectifier using externally mounted phase shifted transformer; no harmonic filter required to meet IEEE 519 guidelines
- DC bus voltage: 3 x 5,000 Vdc
- Power factor greater than 95% in speed control range

Inverter

- Five-level inverter for motor friendly wave form
- Uses 8 IGBT devices for each of three phases
- 6 kV output to motor – no output transformer required
- Inverter power modules water cooled
- Conservative design for expected 20 year MTBF



Motor Control

Frequency Control

- Volt/Hertz Control – standard
- Sensorless vector control - optional

Output Voltage Modulation

The output switching modulation strategy is dynamically adjusted based on three speed zones to minimize motor torque pulsation.

Drive Inputs

- LAN Interface Options: Profibus-DP, DeviceNet, Modbus RTU, TOSLINE
- Input/Output: 6 Analog I/O, 8 Digital I/O

TMdrive-XL75 – 20 MVA Frame



Injection Enhanced Insulated Gate Transistor (IEGT). Rated 4,500 Volts, 2,100 Amps

Power Rating: 20 MVA, expandable to 80 MVA
Output Voltage: 6 kV
Output Frequency: Rated 50-60 Hz, 50 to 250 Hertz

Dimensions: Width 9.4 m
 Height: 2.7 m
Motor type: Synchronous or Induction




Power Input/Output


Input Voltage	Any utility voltage using separate transformer input 50/60 Hz $\pm 2\%$
Output Voltage	5,820 Vac
Output Current	1925 A rms
Output Frequency	50-60 Hz
Output Chopping	600 Hz (max)
Efficiency	98%
Cable Entry	Top or bottom

Clean Motor Output Wave

As a result of the five-level PWM control, the output current waveform is close to a sine wave. Harmonic currents in the motor windings are minimized so the heat loss is negligible and there is very little torque ripple on the output shaft.



Line-to-Line Voltage at 100% Speed



U-phase Current at 100% Speed

Protective Functions Include:

- Inverter overcurrent
- Inverter overvoltage
- Low system voltage
- Motor ground fault
- Motor overload
- Cooling fan abnormal
- Over-temperature
- CPU error
- Water cooling alarm
- Exciter fault
- DC voltage drop
- Motor inverse rotation
- Stall detection
- Ground detection



Power Circuits

Converter

- AC-fed 36-pulse diode rectifier using externally mounted phase shifted transformer; no harmonic filter required to meet IEEE 519 guidelines
- DC bus voltage: 3 x 4,540 Vdc
- Power factor greater than 95% in speed control range

Inverter

- Five-level inverter for motor friendly wave form
- Uses 8 IEGT devices for each of three phases
- 6 kV output to motor – no output transformer required
- Inverter power modules water cooled
- Conservative design for expected 20 year MTBF



Motor Control

Frequency Control

- Volt/Hertz Control – standard
- Sensorless vector control – optional
- Power factor control for synchronous motors

Output Voltage Modulation


The output switching modulation strategy is dynamically adjusted based on three speed zones to minimize motor torque pulsation.

Drive Inputs

- LAN Interface Options: Profibus-DP, DeviceNet, Modbus RTU, ISBus, TOSLINE
- Input/Output: 6 Analog I/O, 8 Digital I/O

TMdrive-XL Series

TMdrive-XL85 – 30 MVA Frame



Gate Commutated Thyristor (GCT) with driver board. Rated 6,000 Volts, 6,000 Amps - the world's largest switching device

Power Rating: 30 MVA, expandable to 120 MVA
Output Voltage: 7.2 kV
Output Frequency: Rated 50-60 Hz, 50 to 200 Hertz

Dimensions: Width 8.1 m
 Height: 2.6 m
Motor type: Synchronous or Induction




Power Input/Output


Input Voltage	Any utility voltage using separate transformer input 50/60 Hz $\pm 10\%$
Output Voltage	7,200 Vac
Output Current	2400 A rms
Output Frequency	50-60 Hz
Output Chopping	600 Hz (max)
Efficiency	98%
Cable Entry	Top or bottom

Clean Motor Output Wave

As a result of the five-level PWM control, the output current waveform is close to a sine wave. Harmonic currents in the motor windings are minimized so the heat loss is negligible and there is very little torque ripple on the output shaft.



Line-to-Line Voltage at 100% Speed



U-phase Current at 100% Speed

Protective Functions Include:

- Inverter overcurrent
- Inverter overvoltage
- Low system voltage
- Motor ground fault
- Motor overload
- Cooling fan abnormal
- Over-temperature
- CPU error
- Water cooling alarm
- Exciter fault
- DC voltage drop
- Motor inverse rotation
- Stall detection
- Ground detection



Power Circuits

Converter

- AC-fed 36-pulse diode rectifier using externally mounted phase shifted transformer; no harmonic filter required to meet IEEE 519 guidelines
- DC bus voltage: 3 x 5,450 Vdc
- Power factor greater than 95% in speed control range

Inverter

- Five-level inverter for motor friendly wave form
- Uses 8 GCT devices for each of three phases
- 7.2 kV output to motor – no output transformer required
- Inverter power modules water cooled
- Conservative design for expected 20 year MTBF



Motor Control

Frequency Control

- Volt/Hertz Control – standard
- Sensorless vector control – optional
- Power factor control for synchronous motors


Output Voltage Modulation

The output switching modulation strategy is dynamically adjusted based on three speed zones to minimize motor torque pulsation.

Drive Inputs

- LAN Interface Options: Profibus-DP, DeviceNet, Modbus RTU, TOSLINE
- Input/Output: 6 Analog I/O, 8 Digital I/O

TMdrive-XL80 – 15 MVA Frame



Gate Commutated Thyristor (GCT) with driver board. Rated 6,000 Volts, 6,000 Amps - the world's largest switching device.

Power Rating: 15 MVA, expandable to 30 MVA
Output Voltage: 3.8 kV
Output Frequency: Rated 50-60 Hz, 50 to 200 Hertz option with derate above 100 Hz
Dimensions: Width 4.8 m; Height: 2.7 m
Motor type: Synchronous or Induction

Power Input/Output

Input Voltage	Any utility voltage using separate transformer input 50/60 Hz ±10%
Output Voltage	3,800 Vac
Output Current	2400 A rms
Output Frequency	50-60 Hz
Output Chopping	600 Hz (max)
Drive Efficiency	98%
Cable Entry	Top or bottom access

A Clean Output Wave

As a result of the three-level PWM control, the output current waveform is close to a sine wave. Harmonic currents in the motor are minimized so the heat loss is negligible and there is very little torque ripple on the output shaft.

Protective Functions Include

- Inverter overcurrent
- Inverter overvoltage
- Low system voltage
- Motor ground fault
- Motor overload
- Cooling fan abnormal
- Over-temperature
- CPU error
- Water cooling alarm
- Exciter fault
- DC voltage drop
- Motor inverse rotation
- Stall detection
- Ground detection

Power Circuits

Converter

- AC-fed 12- or 24-pulse diode rectifier using externally mounted phase shifted transformer; no harmonic filter required to meet IEEE 519 guidelines
- DC bus voltage: 3 x 5,700 Vdc
- Power factor greater than 95% in speed control range

Inverter

- Three-level inverter for motor friendly wave form
- Uses 4 GCT devices for each of three phases
- 3.8 kV output to motor – no output transformer required
- Inverter power modules water cooled
- Conservative design for expected 20 year MTBF

Motor Control

Frequency Control

- Volt/Hertz Control
- Vector control
- Power factor control for synchronous motors

Output Voltage Modulation

The output switching modulation strategy is dynamically adjusted based on three speed zones to minimize motor torque pulsation.

Drive Inputs

- LAN Interface Options: Profibus-DP, DeviceNet, Modbus RTU, TOSLINE S-20
- Input/Output: 6 Analog I/O, 8 Digital I/O

Life Cycle Support from Commissioning to Post Sales Service

TMEIC offers comprehensive Customer Support, from pre-planning, through design, commissioning and post sale service.

**Over 70 Service Engineers
across North America**

**Over 300 Service
Engineers world wide**

Customer Service Call Center

- Open 24x7x365
- Staffed by trained service engineers
- Supported by factory design engineers

Remote Drive and System Diagnostics

- Global Connectivity
- Quick Resolution

Motor and Generator Service

- EASA Service Centers support TMEIC Motors

Commissioning and Customer Training

- Experienced commissioning Team
- Comprehensive factory acceptance test
- Training of the entire team on the system at the factory
- Customized training courses for all TMEIC automation and control systems, drives, motors, generators and other TMEIC products

TMEiC

TMEIC Corporation

Office: 1325 Electric Road, Suite 200
Roanoke, VA, United States 24018
Mailing: 2060 Cook Drive
Salem, VA, United States 24153
Tel.: +1-540-283-2000; Fax: +1-540-283-2001
Email: info@tmeic.com; Web: www.tmeic.com

TMEIC Houston Branch

2901 Wilcrest Dr., Suite 110
Houston, Texas, 77042, USA
Tel: +1-713-784-2163; Fax: +1-712-784-2842
Email: OilGas@tmeic.com; Web: www.tmeic.com

TOSHIBA MITSUBISHI-ELECTRIC INDUSTRIAL SYSTEMS CORPORATION

Mita 43, MT Bldg.
13-16 Mita 3 chome, Minato-ku
Tokyo, Japan, 108-0073
Tel.: +81-3-5444-3828; Fax: +81-3-5444-3820
Web: www.tmeic.co.jp

TOSHIBA MITSUBISHI-ELECTRIC INDUSTRIAL SYSTEMS

(Beijing) CORPORATION
21/F, Building B, In.do Mansion
48 Zhichunlu A, Haidian District
Beijing 100098, PRC
Tel.: +86 10 5873-2277; Fax: +86 10 5873-2208
Email: sales@tmeic.com/china

TMEIC Europe Limited

6-9 The Square, Stockley Park
Uxbridge, United Kingdom, UB11 1FW
Tel.: +44 870 950 7220; Fax: +44 870 950 7221
Email: info@tmeic.eu; Web: www.tmeic.com/europe

TMEIC Industrial Systems India Private Limited

901/D, Filix, L.B.S. Road
Opp Asian Paints, Bhandup
West Mumbai, Maharashtra, India, 400 078
Tel.: +91-40-4434-0000; Fax: +91-40-4434-0034
Email: inquiry_india@tmeic.com; Web: www.tmeic.com/india

TMdrive is a registered trademark of TOSHIBA MITSUBISHI-ELECTRIC INDUSTRIAL SYSTEMS CORPORATION.

All other products mentioned are registered trademarks and/or trademarks of their respective companies. All specifications in this document are subject to change without notice.

All specifications in this document are subject to change without notice. The above brochure is provided free of charge and without obligation to the reader or to TMEIC.

TMEIC Corporation does not accept, nor imply, the acceptance of any liability with regard to the use of the information provided. TMEIC Corporation provides the information included herein as is and without warranty of any kind, express or implied, including but not limited to any implied statutory warranty of merchantability or fitness for particular purposes. The information is provided solely as a general reference to the potential benefits that may be attributable to the technology discussed. Individual results may vary. Independent analysis and testing of each application is required to determine the results and benefits to be achieved from the technology discussed. If you have any questions regarding your project requirements, please contact TMEIC Corporation at 540-283-2301.